

DANLERS

Installation notes

Variants

Low voltage variants can be supplied, coded by the following suffixes:

- 12VAC 12V - (ac supply) operation
- 12VDC 12V - (dc supply) operation
- 24VAC 24V - (ac supply) operation
- 24VDC 24V - (dc supply) operation

Trouble shooting

The COPD cannot be made to switch on during bright days
• The COPD should have the lux set to inactive via the internal mode button (see diagram B)

The PIR does not detect

- Person is too far from the COPD switch, see detection diagram.
- Person is moving unusually slowly (perhaps when testing).

The PIR stops working

- Ensure the unit is mounted correctly so that no water can enter.

The PIR False triggers

- Detector is exposed to air movement on breezy days.

Precautions and Warranty

This product conforms to BS EN 60669-2-1 and BS EN 55015.

Please ensure the most recent edition of the appropriate local wiring regulations are observed and suitable protection is provided e.g. a 10 amp circuit breaker and voltage surge protection. Please ensure that this device is disconnected from the supply if an insulation test is made.

This product is covered by a warranty which extends to 5 years from the date of manufacture.

Products available from DANLERS

- PIR occupancy switches • Daylight linked dimmers • Manual high frequency dimmers
- Photocells • Radio remote controls • Time lag switches • Outdoor security switches
- Dimmers • Heating, ventilation and air-conditioning controls • Bespoke / O.E.M. products

Please call for more information or a free catalogue.

DANLERS Limited, Vincients Road, CHIPPENHAM, Wiltshire, SN14 6NQ, UK.
Telephone: +44 (0)1249 443377 Fax: +44 (0)1249 443388
E-mail: sales@danlers.co.uk Web: www.danlers.co.uk
Company Registered Number 2570169 VAT Registration Number 543 5491 38



Compact person detector, PIR switch

COPD

COPD BK

DANLERS Compact Person Detector is IP66 rated and can be surface mounted onto an external wall. It incorporates a passive infra-red quad sensor to detect movement of a warm body within the detection zone (diagram A) and the COPD (BK) includes a photocell to monitor the ambient light level.

The detection range is about 10 metres over 120 degrees, the range reduces to about 8m at the extremes to prevent nuisance switching.

On detecting movement, if the ambient light is dark enough, the COPD (BK) will switch the load on. The ambient threshold can be set by the user to between approximately 10 and 1000 lux via the internal LUX adjuster (diagrams B and C). The photocell can be disabled via the internal mode button (see overleaf).

If no more movement is detected within a pre-selected time, then the PIR switch will turn the load off. This time lag can be set via the TIME adjuster to 10 seconds, 20 seconds, 40 seconds, 80 seconds, 2 minutes 30 seconds, 5 minutes, 10 minutes, 20 minutes or 40 minutes (diagram D).

Product codes:

COPD Grey enclosure
COPD BK Black enclosure

Loading

The switch should only be connected to a 230V 50Hz AC supply. These PIR switches can switch up to:

- 6 amps (1500W) of resistive loads.
- 6 amps (1500W) of fluorescent loads.
- 3 amps (750W) of electronic and wire wound transformer loads.
- 2 amps (500W) of CFL, 2D lamps, LED Drivers and LED lamps and fittings.
- 1 amp (250W) of fans

Minimum load 2W resistive, suitable for most energy saving lamps, LEDs and emergency fittings.

Installation procedure

1. Please read these notes carefully before commencing work.
In case of doubt please consult a qualified electrician.
2. The detector should be sited so that it is not shaded from daylight
3. The detector should be mounted between 1 and 2.2 metres high, using any of the four pre-drilled mounting holes only.
4. It must be mounted with the cable entering from below.
5. Make sure the power is isolated from the circuit.
6. The detector should be connected as shown in diagram E
L - Live in, N - Neutral in, SL - Switched Line out.
7. IMPORTANT - Replace terminal cover.
8. Once the wiring has been completed and verified, switch on the supply and test the operation.

Lux and Time set-up

For convenience, ensure that the TIME is set to minimum when setting up the LUX level. Afterwards set the TIME to a value suitable for the application.

8. When powered up, (after 1 minute stabilisation time) turn lux pot (diagram C) fully clockwise and time pot fully anticlockwise.
9. Press the MODE button (diagram B) for approximately 0.5s. The LED will go green indicating the LUX cell is active. (Or press and hold button for approx. 4 seconds – LED goes RED indicating Lux cell INACTIVE). Repeating these steps will toggle the functionality.
10. If lux cell active, vacate area until PIR switch switches the load off (should be after 10 seconds).
11. With the LUX as desired on working plane from daylight ONLY (no artificial light), wind the lux pot anticlockwise whilst waving your hand in front of the PIR cell. When the PIR switches the load ON, stop turning the pot. The Lux inhibit level is now set.
12. Turn the PIR time to the desired timeout (diagram D). Whenever a person is detected, the time lag will start again and the load will stay switched on.

Precondition	Power-up Condition
Lux Cell Inactive Relay OFF	Lux Cell Inactive Relay comes ON for 1 Min. After 1 min. ready for detection.
Lux Cell Active Relay ON	Lux Cell Active Relay stays ON for 1 Min. After 1 min. ready for detection.
Lux Cell Active Relay OFF	Lux Cell Active Relay comes ON for 1 Min. After 1 min. ready for detection.
Lux Cell Inactive Relay ON	Lux Cell Inactive Relay stays ON for 1 Min. After 1 min. ready for detection.

