


LAMP SPECIFICATIONS:	
Nominal Wattage	26W
Rated Wattage	26W
Average lifetime hours	8,000 hrs
Nominal useful luminous flux	<b>1716 lm</b>
Rated luminous flux	1716 lm
Luminous efficacy (Lm/W) in 50Hz operation	66
Rated lamp Lumen maintenance	2000hrs: 85% 4000 hrs: 78% 8000 hrs: 75%
Rated survival factors	2000hrs: 98% 4000 hrs: 90% 8000 hrs: 50%
Lamp dimensions (mm)	34 x 34 x 170
Cap type	G24q-3
Lamp Mercury content to an accuracy of 0.1mg	2mg
Colour rendering index Ra	≥80
Colour temperature	6400K
Ambient temperature required to achieve maximum luminous flux	25°C
Dimmable	No

**Eterna** SL226W



This luminaire is compatible with bulbs of the energy classes:




This luminaire is sold with a bulb of the energy class: **A**

874/2012



**Eterna** SL226W



**28.60** kWh/1000h

#### EVENTUALLY, YOU MAY WANT TO REPLACE THIS PRODUCT:

Regulations require the recycling of Waste from Electrical and Electronic Equipment (European "WEEE Directive" effective August 2005—UK WEEE Regulations effective 2nd January 2007). Environment Agency Registered Producer: WEE/ GA0248QZ.

WHEN YOUR PRODUCT COMES TO THE END OF ITS LIFE OR YOU CHOOSE TO REPLACE IT, PLEASE RECYCLE IT WHERE FACILITIES EXIST - DO NOT DISPOSE WITH HOUSEHOLD WASTE.

#### IF YOU EXPERIENCE PROBLEMS:

If you believe your product is defective, please return it to the place where you bought it. Our Technical Team will gladly advise on any Eterna Lighting product, but may not be able to give specific instructions regarding individual installations.

For breakage information visit:  
[www.etera-lighting.co.uk](http://www.etera-lighting.co.uk)



Issue 2014



#### FOR PRODUCT ADVICE:

• T: 01933 673 144  
• F: 01933 678 083  
• E: [sales@etera-lighting.co.uk](mailto:sales@etera-lighting.co.uk)

Visit our website:

[www.etera-lighting.co.uk](http://www.etera-lighting.co.uk)



## INSTALLATION INSTRUCTIONS

**A guide for qualified electricians**



**Model:**  
**SL226W**

**2 x 26W Low Energy Floodlight**

#### Pack contents:

1 x fitting  
2 x 26W compact fluorescent lamps  
1 x bracket

These instructions are provided as a guideline to assist you.

**PLEASE READ THESE INSTRUCTIONS BEFORE USING YOUR NEW FITTING**  
**PLEASE RETAIN FOR FUTURE REFERENCE**

## READ THIS FIRST:

Check the pack and make sure you have all of the parts listed on the front of this booklet. If not, contact the outlet where you bought this product.

This product contains glass, care must be taken when assembling, fitting or handling to prevent personal injury or damage to the product.

**This product must be installed by a competent person in accordance with the current building and IEE wiring regulations.**

As the buyer, installer and/or user of this product it is your own responsibility to ensure that this fitting is fit for the purpose for which you have intended it. Eterna Lighting cannot accept any liability for loss, damage or premature failure resulting from inappropriate use.

Switch off the mains before commencing installation and remove the appropriate circuit fuse or lock off MCB.

The lamps supplied with this fitting are consumable parts and therefore may be outside of any warranty offered.

This unit is suitable for outdoor use.

Before making fixing hole(s), check that there are no obstructions hidden beneath the mounting surface such as pipes or cables.

Make sure that the fixings are strong enough to support the considerable weight of the fitting and hold it rigidly.

When choosing the location for your new fitting, give consideration to the ease of lamp changes. The fitting should not be installed in a position where it will be difficult to reach and ensure that the fixings will be anchored in a solid surface e.g. concrete, brick or a joist—do not fix directly onto panelling or cladding etc.

When making connections ensure that the terminals are tightened securely and that no strands of wire protrude. Check that the terminals are tightened onto the bared conductors and not onto any insulation.

This product must be connected to earth.

**WARNING: This product becomes hot!**

You are advised at every stage of your installation to double-check any electrical connections you have made. After you have completed your installation there are electrical tests that should be carried out, these tests are specified in the current IEE wiring and building regulations.

## CLEANING:

Disconnect the power and clean the exterior only of this fitting with a moist (not wet) cloth.

Do not use any chemical or abrasive cleaners.

## LAMP REPLACEMENT:

- 1) Switch off the electricity at the mains.
- 2) Release the front cover by unscrewing the 4 fixing screws, taking care not to lose the "O" rings.
- 3) Remove the lamp by pulling gently away from the lampholder and lifting free.
- 4) Fit replacement lamp by pushing it into the lampholder and refit the front cover.

## REPLACEMENT LAMP TYPE:

Requires 2 x 26W G24q-3 double turn D4 pin CFL (included).

Fitting is rated at 26W max (per lampholder).

## INSTALLATION:

- 1) Choose the location for your floodlight taking care to comply with the conditions listed above.
- 2) Select suitable fixings (not supplied).
- 3) Remove the nut and bolt from each end of the mounting points and separate from the fitting.
- 4) Mark the position of the fixing holes using the bracket as a template. Check that the hole positions are level with a spirit level.
- 5) Secure the bracket in position.
- 6) Offer the fitting up to the bracket.
- 7) Replace the nuts and bolts at each end of the bracket and tighten securely.
- 8) Make the connections to the mains supply. If you are making your connection outdoors, you will need to use a watertight connection box (not supplied).
- 9) Restore power and switch on.

