

| NED/3 Emergency Output Chart | | |
|------------------------------|------------------------|---------------------------|
| Load Voltage | Em Wattage (EOF Watts) | Em Current (EOF Milliamp) |
| 6 | 1.92 | 320 |
| 7 | 2.10 | 300 |
| 8 | 2.24 | 280 |
| 9 | 2.34 | 260 |
| 10 | 2.40 | 240 |
| 11 | 2.42 | 220 |
| 12 | 2.40 | 200 |
| 13 | 2.47 | 190 |
| 14 | 2.52 | 180 |
| 15 | 2.55 | 170 |
| 16 | 2.56 | 160 |
| 17 | 2.57 | 151 |
| 18 | 2.57 | 143 |
| 19 | 2.57 | 135 |
| 20 | 2.56 | 128 |
| 21 | 2.54 | 121 |
| 22 | 2.55 | 116 |
| 23 | 2.53 | 110 |
| 24 | 2.59 | 108 |
| 25 | 2.58 | 103 |
| 26 | 2.57 | 99 |
| 27 | 2.57 | 95 |
| 28 | 2.55 | 91 |
| 29 | 2.52 | 87 |
| 30 | 2.49 | 83 |
| 31 | 2.48 | 80 |
| 32 | 2.50 | 78 |
| 33 | 2.51 | 76 |
| 34 | 2.52 | 74 |
| 35 | 2.56 | 73 |
| 36 | 2.56 | 71 |
| 37 | 2.55 | 69 |
| 38 | 2.55 | 67 |
| 39 | 2.54 | 65 |
| 40 | 2.52 | 63 |
| 41 | 2.50 | 61 |
| 42 | 2.48 | 59 |
| 43 | 2.45 | 57 |
| 44 | 2.42 | 55 |
| 45 | 2.39 | 53 |
| 46 | 2.35 | 51 |
| 47 | 2.35 | 50 |
| 48 | 2.30 | 48 |
| 49 | 2.30 | 47 |
| 50 | 2.30 | 46 |
| 51 | 2.35 | 46 |
| 52 | 2.34 | 45 |
| 53 | 2.33 | 44 |
| 54 | 2.32 | 43 |
| 55 | 2.31 | 42 |
| 56 | 2.35 | 42 |
| 57 | 2.34 | 41 |
| 58 | 2.32 | 40 |
| 59 | 2.36 | 40 |
| 60 | 2.34 | 39 |
| 61 | 2.32 | 38 |
| 62 | 2.29 | 37 |
| 63 | 2.27 | 36 |
| 64 | 2.24 | 35 |
| 65 | 2.28 | 35 |
| 66 | 2.24 | 34 |
| 67 | 2.21 | 33 |
| 68 | 2.24 | 33 |
| 69 | 2.21 | 32 |
| 70 | 2.24 | 32 |
| 71 | 2.20 | 31 |
| 72 | 2.23 | 31 |
| 73 | 2.19 | 30 |
| 74 | 2.22 | 30 |
| 75 | 2.25 | 30 |
| 76 | 2.20 | 29 |
| 77 | 2.23 | 29 |
| 78 | 2.18 | 28 |
| 79 | 2.21 | 28 |
| 80 | 2.24 | 28 |