

# LED PLL Retrofit





Energy saving LED PLL Retrofit lamp for direct retrofit with no rewiring - ideal for multiple commercial applications. Compatible with a range of common electronic ballasts\*. Featuring a full glass body with same dimensions as CFL PLL. No mercury or hazardous materials. Instant start with no warm-up time.

- 40,000 hour life
- 15,000 switching cycles
- 4000K cool white
- Colour rendering index Ra≥80
- 2G11 cap
- Opal white finish
- Not suitable for dimming
- Not suitable for emergency circuits
- For indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Total Lumens (lm)	CFL Equivalent (W)	Dimensions (mm)			Energy Rating	Order Qty
								Dia	H	L		
<b>Single Carton</b>												
5273	25	240	2G11	Cool White	4000	2700	55	43	24	536	A+	1

\* See below pages for list of compatible electronic ballasts. The performance of this lamp is determined by the fitting to which it is installed.



Experts in lighting since 1878

# LED PLL Retrofit Ballast Compatibility



This lamp is a direct retrofit and works with most existing ballasts with no re-wiring. However Crompton Lamps have extensively tested the below ballasts to evaluate their function and to make sure the ballast meets our compatibility standards.

The below table is designed to help you choose a suitable ballast for your Crompton Lamp product.

For guidelines on ballasts not listed below, or for more information please contact Crompton Lamps.

Tested Products: 5273

Manufacturer	Ballast Model	Product Codes 5273	Notes
<b>Single Ballast</b>			
BAG Electronics	BCS54.1FX-11/220-240 1 X T5 54W & 1 CFL 55W & 1 X T8 58W	✓	
BAG Electronics	BCS55. 1Q-01/220-240/T5C	✓	
EFA	HFL15458E 1X54W T5 1X55W PLL 1X58W T8	✓	
EFA	HFL15458E 1X54-58W Multi 100-277V	✓	
ELT	BE 258-2 2 X 58W T8	✓	
Osram	QTP-OPTIMAL 1X54...58	✓	Flashes on/off a few times when the unit is switched off
Philips	HF-P 154/155 TL5 HO/PL-L III IDC	✗	
Philips	HF-P 155 PL-L III 220-240V 1X55W	✓	
Philips	HFP158TLD 1X58W NON-DIM	✓	
Tridonic	PC 1/55 TCL PRO	✓	
Tridonic	PC 1x80 T5 PRO Ip 1x80W HF	✓	
<b>Twin Ballast</b>			
BAG Electronics	BCS54.2FX-11/220-240 2 X T5 54W & 2 X CFL 55W	✓	
ELT	BE 258-2 2 X 58W T8	✓	
Osram	QTPDL255 2X55W PLL HF	✗	
Osram	QTP-OPTIMAL 2X54...58 2 X 58W 240V	✓	
Philips	HF-P 254/255 TL5 HO/PL-L III 2X 54W T5/ 55W PL-L	✓	
Philips	HF-P 258 TL-D III 220-240V 2X58W NON-DIM	✓	
Tridonic	PC 2 x 55 TCL Pro Ip 2 x 55W HF	✓	

Crompton Lamps 25W LED PLL has been tested on the above listed ballasts and the table indicates whether the ballast passes our internal compatibility tests where indicated. Ballasts that do not appear on the list might still be compatible but have not been tested. We are continuously testing for compatible ballasts. Please check back for updates. The performance of this lamp is determined by the fitting to which it is installed.

Experts in lighting since 1878